Greg Feild
Ace School
1/15/2004

Triggers and Scalers

Greg Feild
Ace School
1/15/2004

Triggers and Scalers

RUN II TRIGGER SYSTEM

CMU, CMP,CMX, IMU

Detector Elements

CCAL

WCAL

PCAL

| CAL | COT | MUON | SVX | CES |

CLC | TOF | BSC

XFT | MUON PRIM. | XCES

SMXR

XTRP

DIRAC

| L1 CAL | L1 TRACK | L1 MUON |

MUTRG

FRED

GLOBAL LEVEL 1

DCAS

L2 CAL

SVT

ALPHA

GLOBAL LEVEL 2

TSI/CLK

TS, TXPT, RXPT

Trigger rate reductions

– Crossing rate
  - 36x36 bunches, 396 ns
  - 1.7 MHz
– Level 1
  - Synchronous, pipelined
  - 40 (17) kHz accept rate
– Level 2
  - Asynchronous, buffered
  - 300 Hz accept rate
– Level 3
  - PC farm
  - 75 Hz accept rate

HRR Halts, Resets and Restarts the L1 Pipeline

Dataflow of CDF "Deadtimeless" Trigger and DAQ

Detector — 7.6 MHz Crossing rate / 132 ns clock cycle

L1 Storage Pipeline: 42 Clock Cycles Deep

Level1:
7.6 MHz Synchronous pipeline
5544ns latency
<50 kHz Accept rate

L1 trigger

L1 Accept

L2 Buffers: 4 Events

Level 2:
Asynchronous 2 stage pipeline
~20µs latency
<1kHz Accept Rate

L2 trigger

L2 Accept

L1+L2 rejection: 10,000:1

DAQ Buffers

L3 Farm

Mass Storage

PJW 6/2/98

The Trigger System Interface

Components

- The Global Level 1 Trigger
- The Trigger Supervisor
- The Trigger Crosspoints
- The Return Crosspoints
- The Scalers

The Global Level 1 Trigger – b0l1gl00

- a.k.a FRED
- Forms 64 L1 triggers every 132 ns
- Data from calorimeter, muons, tracking, CLC, TOF, diffractive
- Sends preliminary L1 decision to the Trigger Supervisor
- Sends 64 L1 trigger bits to Level 2 crate
- Sends trigger data to scalers for rate accounting
- Ace Monitors trigger rates on "Rates and Deadtimes" GUI
  - Cosmic rate ~ 50 Hz
  - Level 1 design rate = 40 kHz
  - Bunch Crossing rate = 1.7 MHz
- CO checks trigger performance with TrigMon, XMon

The Trigger Supervisor (TS) – b0tsi00

- Controls the synchronous flow of event data from the Front-End crates to the Event Builder (EVB)
- Manages the filling and readout of the four Level 2 buffers
- Receives L1A/R recommendation from FRED
- Sends out the final L1 decision based on L2 buffer availability
- Receives the L2 decision from the L2 (Alpha) crate and sends it to the Front-End crates
- The Trigger Manager process sends TS event data to the EVB
- TS sends Livetime accounting signals to the Scaler crate
- The TS can also control the Front-End independently of the Trigger
  - Auto L1 Accept in "calib continuous" mode
  - L1 Accept based on external calibration signals
  - Auto L2 Accept
- There are 8 Trigger Supervisors

There are many different ways to trigger and readout

1. Standard or Physics
   - Standard (Fred)
   - L2 Processors
   - VRB (HardEvb)

2. Null or DAQ Test
   - Calib Continuous
   - Auto L2 Accept
   - Ethernet (SoftEvb)

3. Other combinations

Note: There are "TS Auto L2 Accept" and "Alpha Auto L2 Accept" modes!

The Trigger Crosspoints (TXPT) – b0tsi01

- Routes TS messages (L1A, L2A, HRR) to the Tracers in the Front-End crates
- Responsible for partitioning the detector
- Allows subsets of the ~ 120 Front-End crates to be controlled by different Trigger Supervisors
- There is only one "Physics" partition; I.e. the Trigger cannot be partitioned
- Note: Each crate is always listening to one partition!

The Return Crosspoints (RXPT) – b0tsi02

- Monitors DONE, ERROR, and BUSY signals from the Tracers in the Front-End crates
- DONE de-asserted on receipt of L2 Accept and re-asserted when data readout is complete
- DONE timeout occurs when this take too long
- BUSY signal sent to RXPT if Tracer/VRB is not ready for another L2A
- BUSY timeout indicates problem at the VRB/EVB interface
- ERROR sent to RXPT from the Tracer if something goes wrong in a Front-End crate
- The ERROR feature is not widely used …
- The ACE monitors Return Crosspoint activity on the DAQMon "RXPT" GUI

The Scaler Crate – b0tsi03

- Provides L1 trigger rates from FRED data
- Provides global L1 and L2 accept rates from the TS
- Provides Livetime and Deadtime accounting form the TS
- Information displayed in real time on "Rates and Deadtimes" GUI
- Scaler data also readout on each L2 Accept and sent to Xmon

SCRAMNet to EVB

RXPT (b0tsi02)

CLOCK

FRED (b0l1gl00)

SCALERS (b0tsi03)

TS (b0tsi00)

TXPT (b0tsi01)

The Trigger System Interface

The Trigger System Interface (TSI)

The RXPT Monitor

Available from DAQMON. Click on RXPT and then select the partition.

Front-end crates are usually not the cause of BUSY Deadtime (e.g. svx02, tsi03)

Return Crosspoints Partition 0

Partition **0** is **IDLE** – Last update: 16:10:18

DONE	ERROR	BUSY
Realtime NOT DONE (1000.0 ms elapsed)	Realtime ERROR	Realtime BUSY (0.0 ms elapsed)
(N=0)	`cal06;wcal07;wcal00;puls01;htdc00;(N=23)	(N=0)
Crates DONE last	Crates with latched ERROR	Crates with latched BUSY
wcal02;(N=1)	puls01;htdc00;(N=2)	(N=0)
Crates not responding		
(N=0)		
Timeout Encountered! Not running yet	Error Encountered! ERROR is latched	No Timeout Condition Not running yet

Look here for the offending crate(s) if you have high READOUT Deadtime

Look here when a run fails to start with b0tsi00 going RED and messages like "TS L2 FSM failed to start" . Usually a front-end crate is pulling CDF_ERROR

More on the Scalers

- The Scalers are banks of counters with VME readout. These hardware scalers do the TSI accounting
  - Livetime/Deadtime accounting
  - Level 1 trigger rates (GFRED gated)
  - Buffer occupancy, etc.
- There are also "software" scalers
  - Level 1 trigger rates (GLIVE gated)
  - Level 2 trigger rates
  - Level 3 trigger rates

Deadtime

- Deadtime occurs when the Trigger Supervisor must send a Level 1 reject regardless of what the trigger tells it to do
- Deadtime (> 5%) is bad!

Deadtime/Livetime accounting

- Input signals to Deadtime/Livetime accounting include
    - CDF_CLK – the basic unit of time
    - CDF_BC – gate indicating a filled crossing
    - CDF_ABORT – gate marking crossings in the abort gap
    - BUSY – from the VRBs via the Tracer
    - INHIBIT – trigger inhibit
    - TS_RUN – as in Halt/Recover/Run
    - TS_PAUSE – from the PAUSE button on the Run Control GUI
    - L2BF_EMPTY – Internal TS signal marker indicating at least one free buffer

Definition of Deadtime/Livetime signals

- Runtime gate: GRUN = $\overline{TS\_RUN} * \overline{TS\_PAUSE} * CDF\_BC * \overline{CDF\_ABORT}$

- Livetime Gate: GLIVE = GRUN * L2BF_EMPTY * $\overline{INHIBIT}$

- Fredtime Gate: GFRED = GRUN * $\overline{INHIBIT}$

- DEADTIME = RUNTIME - LIVETIME

Accounting signals

- RUNTIME = GRUN*CDF_CLK

    Counts each filled crossing the DAQ is enabled to run

- LIVETIME = GLIVE*CDF_CLK

    Counts each filled beam crossing the DAQ is enabled to run and is not forced to send Level 1 rejects

- DEADTIME = RUNTIME - LIVETIME

Sources of Deadtime

- **INHIBIT_DEAD: Usually an HV trip**
- **No free Level 2 buffers**
  - BUSY_DEAD: A VRB is filling up. Check EVB status
  - L1DONE_DEAD: Waiting for L1_DONE from SRC. Check Silicon status
  - L2_DEAD: All 4 buffers full. Waiting for L2 decision from Alpha. Page L2 expert.
  - READOUT_DEAD: 4 L2 accepts issued. Front-end crate(s) slow to respond. Find slow crate with RXPT monitor
  - TSI_DEADTIME: Time lost due to TS book-keeping. Very rare. Can occur instead of BUSY deadtime when running without Silicon. Check EVB.
- **Level 2 buffers will fill up if the L1 accept rate is too high**

The Scaler Monitor – Note distinction between L1A and Fred L1A

The Scaler Monitor

There are two Level 1 rates displayed: "L1 Accept" and "Fred L1A".
In the limit of 0% Deadtime they should be the same.

Fred L1A is the rate at which the detector/trigger is trying to drive
the system. This is the L1A rate to note during a SPIKE run, for example.

The L1 Accept rate is the actual trigger rate seen by the Front-end crates
and is governed by L2 buffer availability.

Also note: Even when the Total Deadtime is quite small (1%), the
individual contributions to the Deadtime add to 100%.

PreFRED trigger rates

	CDF Trigger Rate Monitor							

PreFRED trigger rates

CDF Trigger Rate Monitor

Update again! | **Trigger Rate Monitor 16:24:44** | **Dynamic Prescaling Disabled** | **Stored Run Info**

Partition: 0
Trigger Type: PHYSICS_1_04 [4,255,357]

Run Number: 161011
Event Number: 468308100

Runtime: 34,739.3s
Livetime: 33,942.5s

Select Run: 161011

Tabs: General | PreFred | Fred | Fred Prescaled | Fred Live | TS | L2 (0-63) | L2 (64-127) | L3 (0-63) | L3 (64-127) | L3 (128-191) | L3 (192-255) | DynamicPrescale

n	Trigger	Count	<Rate>	Rate, Hz	Rate (log scale)	n	Trigger	Count	<Rate>	Rate, Hz	Rate (log scale)
0	L1_JET5 [1]	225,646,176	6,515.7	6,515.7		32	L1_JET5 [1]	225,646,176	6,515.7	6,515.7	
1	L1_BMU_LO_BSUR_TSU0 [1]	16,478,506	475.8	475.8		33	GAP_EAST [1]	26,324,297,906	760,136.9	760,136.9	
2	L1_MB_CLC [1]	21,039,331,932	607,528.9	607,528.9		34	GAP_WEST [1]	25,820,101,317	745,577.8	745,577.8	
3	L1_BMU_LO_BSU_PT3.3 [1]	1,604,109	46.3	46.3		35	L1_TWO_CJET5 [1]	9,799,935	283.0	283.0	
4	L1_SEVEN_TRK2 [2]	2,530,499	73.1	73.1		36	L1_TWO_TRK2 [2]	682,411,464	19,705.2	19,705.2	
5	L1_CEM4_PT4 [1]	14,043,357	405.5	405.5		37	L1_TWO_TRK6_DPHI30 [1]	1,701,593	49.1	49.1	
6	L1_CMX1.5_PT2_CSX [2]	6,769,824	195.5	195.5		38	L1_TRK4 [1]	275,649,106	7,959.6	7,959.6	
7	L1_CEM8_PT8 [3]	880,612	25.4	25.4		39	L1_CMUP6_PT4 [1]	1,074,675	31.0	31.0	
8	L1_TRK3 [1]	856,103,224	24,720.7	24,720.7		40	L1_CMU1.5_PT1.5 [1]	68,778,966	1,986.1	1,986.1	
9	L1_TRK7 [1]	41,274,595	1,191.8	1,191.8		41	L1_CMX1.5_PT2_CSX [2]	6,769,824	195.5	195.5	
10	L1_TWO_TRK2_DPHI90 [1]	444,208,380	12,826.9	12,826.9		42	L1_CMX6_PT8_CSX [2]	62,059	1.8	1.8	
11	L1_TWO_TRK2_OPPQ_DPHI135_	163,548,395	4,722.6	4,722.6		43	L1_TWO_CMU1.5_PT1.5 [1]	576,100	16.6	16.6	
12	L1_EM8 [1]	10,273,348	296.7	296.7		44	L1_COT_SPIKE [1]	0	0.0	0.0	
13	L1_CMU1.5_PT1.5 [1]	68,778,966	1,986.1	1,986.1		45	L1_MET15 [1]	4,357,486	125.8	125.8	
14	L1_CMX1.5_PT2_CSX [2]	6,769,824	195.5	195.5		46	L1_TWO_TRK2 [2]	682,411,464	19,705.2	19,705.2	
15	L1_MET15 [1]	4,357,486	125.8	125.8		47	L1_MET25 [1]	163,476	4.7	4.7	
16	MB_CLC [1]	21,039,331,932	607,528.9	607,528.9		48	MB_RP [1]	507,255,687	14,647.4	14,647.4	
17	L1_TWO_TRK2 [2]	682,411,464	19,705.2	19,705.2		49	L1_TWO_TRK10_DPHI20 [2]	369,761	10.7	10.7	
18	L1_JET5 [1]	225,646,176	6,515.7	6,515.7		50	L1_TWO_TRK2.5_OPPQ_DPHI135_	67,835,629	1,958.8	1,958.8	
19	GAP_EAST [1]	26,324,297,906	760,136.9	760,136.9		51		0	0.0	0.0	
20	MB_RP [1]	507,255,687	14,647.4	14,647.4		52		0	0.0	0.0	
21	GAP_WEST [1]	25,820,101,381	745,577.8	745,577.8		53		0	0.0	0.0	
22	L1_JET10 [1]	15,397,443	444.6	444.6		54		0	0.0	0.0	
23	MB_XING [1]	59,401,362,700	1,715,265.9	1,715,265.9		55		0	0.0	0.0	
24	L1_JET10 [1]	15,397,443	444.6	444.6		56		0	0.0	0.0	
25	L1_SUMET90 [1]	1,479,162	42.7	42.7		57		0	0.0	0.0	
26	L1_TAU0_PT4 [1]	276,567,908	7,986.1	7,986.1		58		0	0.0	0.0	
27	L1_CEM2_PT2_MINUS [1]	202,202,190	5,838.8	5,838.8		59		0	0.0	0.0	
28	L1_CEM2_PT2_PLUS [1]	168,295,907	4,859.7	4,859.7		60		0	0.0	0.0	
29	L1_TWO_CEM2 [1]	213,484,769	6,164.6	6,164.6		61		0	0.0	0.0	
30	L1_TWO_CEM4_PT4 [1]	572,660	16.5	16.5		62		0	0.0	0.0	
31	L1_CMU0_PT4 [1]	276,567,908	7,986.1	7,986.1		63		0	0.0	0.0	